US005367664A

United States Patent [19]

Magill et al.

[11] **Patent Number: 5,367,664**

[45] **Date of Patent: Nov. 22, 1994**

[54] **ELECTRONIC DOCUMENT INTERCHANGE TEST FACILITY**

[76] Inventors: **James W. Magill**, 104 Lily Ct., Allen, Tex. 75002; **Kathleen M. Adams**, 6823 Winding Rose Trail, Dallas, Tex. 75252; **Fred A. Sammet**, 2801 Rigsbee Dr., Plano, Tex. 75074-4707

[21] Appl. No.: **753,265**

[22] Filed: **Aug. 30, 1991**

[51] **Int. Cl.**^{5} **G06F 1/00**

[52] **U.S. Cl.** **395/575; 364/226.4**

[58] **Field of Search** 395/575; 364/408, 250, 364/225.8, 226.4

[56] **References Cited**

U.S. PATENT DOCUMENTS

4,799,156	1/1989	Shavit et al.	364/408
4,951,196	8/1990	Jackson	364/401
5,202,977	4/1993	Pasete, Jr. et al.	364/200

FOREIGN PATENT DOCUMENTS

2278368	of 1990	Japan	G06F 15/38
3218540	9/1991	Japan	G06F 11/28

OTHER PUBLICATIONS

David Spooner 'A data Translation Tool for Engineering Systems' 1989 pp. 96–104.

Meera M. Blattner et al. 'A User Interface for computer-Based Message Translation' 1989 pp. 43–51 Ref. (AB).

Meera M. Blattner et al. 'A Visual Interface for Generic Message Translation' 1988 pp. 121–126 Ref. (AA).

Hwa-Yea Chang et al. 'Circuit simulation and Modeling' 1990 pp. 8–13.

Primary Examiner—Robert W. Beausoliel
Assistant Examiner—Albert Decady
Attorney, Agent, or Firm—Tammy L. Williams; Richard L. Donaldson

[57] **ABSTRACT**

A method and system for electronic data interchange (EDI) translation testing displays a plurality of operator-interactive panels for controlling pre-production translation of EDI document files. The EDI Test Facility integrates numerous translator programs to detect translation errors. Once an error is detected, the EDI test facility displays the translation error and permits an operator to interactively correct the segment of the EDI document file containing the error. Once the error is corrected, the EDI Test Facility permits retranslation of the segment. When correctly translated, the segment is added to all previously corrected segments of the EDI document file in a working file. The method and system continue until stopped by the operator or EDI document file translation is complete.

7 Claims, 4 Drawing Sheets


FILL IN PANEL FOR CONFIGURATION FILES
74
FILL IN PANEL FOR INPUT, WORK, SEGMENT, AND LOG FILES. DISPLAY ERROR MESSAGES
76
FILL IN TRANSLATOR CONFIGURATION PANEL
78
84
SEND TRANSLATION SUCCESSFUL MESSAGE TO SCREEN
TRANSLATE DATA
82
80
ERROR FOUND
NO
YES
ISSUE SCREEN WITH INFORMATION MESSAGES AND UNDER EDIT FACILITY AND LOG PROBLEM
86
MAKE CHANGES TO DATA
88
YES
ANY CHANGES MADE
NO
90



```
——————————————— TRANSLATOR CONFIGURATION ———————————————
COMMAND  ===>.                                   .SCROLL ===>.CSR .
Enter/Verify EDI Parameters Below:

Program===>.                           (Translator Name)
Plan    .===>.                         (DB2 Plan)
Steplib .===>.                        .(Full Name, No Quotes)
        .===>.                        .(Full Name, No Quotes)
Parms   .===>.                        .(Translator Parms)
Again   .===>.                        .(Yes/No, Default=Yes)



914C/G 361 1 5 15        ADATSAGT  KBD    a      Printing
```

FIG. 1



```
——————————————— TEST FACILITY ———————————————
COMMAND  ===>.                                   .SCROLL ===>.CSR .
Enter/Verify EDI Parameters Below:
Input   .===>.AAAP.EDI.I.XPCWMRT             .(Full Name, No Quotes)
Work    .===>.DAMMSBG.WORK                   .(Full Name, No Quotes)
Segment.===>.DAMMSBG.SEGMENT                 .(Full Name, No Quotes)
Log     .===>.DAMMSBG.LOG                    .(Full Name, No Quotes)

Sgmt   Error
Number Explanation
************************** BOTTOM OF DATA **************************



914C/G 361 1 5 16          ADATSAGL       a       Printing
```

FIG. 2



```
---------------------------- TEST FACILITY ---^TRANSLATION INCOMPLETE^
COMMAND  ===>^                                      ^SCROLL ===>^PAGE^
Enter/Verify EDI Parameters Below:

Input   ^===>^DAMMKMM.FB.DATA                  ^(Full Name, No Quotes)
Work    ^===>^DACCJBM.WORK                     ^(Full Name, No Quotes)
Segment^===>^DACCJBM.SEGMENT                   ^(Full Name, No Quotes)
Log     ^===>^DACCJBM.LOG                      ^(Full Name, No Quotes)

Sgmt    Error
Number Explanation
000003^^ERR14 ,Bad sql return code -924..
**************************** BOTTOM OF DATA ****************************





. . . . . . . . . . . . . . . . . . . . . . . . . . . . . . . . . . . .
914C/G 361 1 5 16          ADATSAIY       a       Printing      11:06:28
```

FIG. 3



```
EDIT ——— DACCJBM.SEGMENT ————————————— COLUMNS 001 072^
COMMAND  ===>^                                ^SCROLL ===>^CSR^
RESULTS OF TRANSLATION:
Standard:^ANSI  ^Release:^00200^Version:^002001    ^Agency:^X ^
Last Segment Processed Successfully:^000002^
Reason:^ERR14 ,Bad sql return code -924..
Correct Identified Errors And Hit PF3 To Retranslate
_______________________________________________________________^
***************************** TOP OF DATA *****************************
000001^ISA*00*          *00*         *01*009122532        *01*007321904     *91
000002^GS*PO*153647706*007321904*910806*1937*1189*X*002001^
000003^ST*850*8114065^
000004^BEG*00*SA*38114065***910806**91-29A^
000005^TAX*03-04737-006***********3^
000006^N1*BY*COLORADO TELECOMMUNICATION DIV*92*38010000^
000007^PER*BD*GARY THOMSEN*TE*719-531-4248^
000008^N1*AK*COLORADO TELECOMMUNICATION DIV*92*38010101^
000009^N1*ST*COLORADO TELECOMMUNICATION DIV*92*38010201^
000010^N1*BT*COLORADO TELECOMMUNICATION DIV*92*38010001^
000011^N1*SE*TEXAS INSTRUMENTS INC^
000012^PO1*1*900*EA*0.29**BP*1826-1439*VP*TLC555CP^
000013^SCH*900*EA****002*910930^
000014^TD5*O*92*09******SB*VD*5^
. . . . . . . . . . . . . . . . . . . . . . . . . . . . .
914C/G 361 1 5 15          ADATSAIY      a        Printing         11:05:56
```

FIG. 4


FILL IN PANEL FOR CONFIGURATION FILES
74
FILL IN PANEL FOR INPUT, WORK, SEGMENT, AND LOG FILES. DISPLAY ERROR MESSAGES
76
FILL IN TRANSLATOR CONFIGURATION PANEL
78
84
SEND TRANSLATION SUCCESSFUL MESSAGE TO SCREEN
TRANSLATE DATA
82
80
ERROR FOUND
NO
YES
ISSUE SCREEN WITH INFORMATION MESSAGES AND UNDER EDIT FACILITY AND LOG PROBLEM
86
MAKE CHANGES TO DATA
88
YES
ANY CHANGES MADE
NO
90

FIG. 5

ELECTRONIC DOCUMENT INTERCHANGE TEST FACILITY

TECHNICAL FIELD OF THE INVENTION

The present invention relates to the methods and systems for testing the transmission of data and more particularly, to a method for testing the transmission of electronic data interchange (EDI) documents files.

BACKGROUND OF THE INVENTION

In recent years many companies, in trading with other companies, for the transmission and receipt or interchange of business information have come to use computerized systems known as electronic data interchange or EDI systems. EDI systems enjoy the particular advantage of having an established set of standards applicable to various types of business documents. For example, in an EDI system, an invoice has a defined format and, as a result, may be rapidly transmitted between trading partners as a compact data file from the sending trading partner's computer to the receiving trading partner's computer. To create the compact data files, an EDI operator must first translate the EDI documents. The EDI document files are compact data files that the receiving trading partner receives. These compact data files are translated back into documents by the receiving trading partner.

Applications for EDI methods and systems include business activities such as purchasing, accounts payable and accounts receivable functions, banking transactions, electronic funds transfer and other document transfers. Other EDI system applications include order filling and processing between trading partners. Not only is this helpful in buying and selling goods, but also trading partners that are transportation companies may use this information to maximize the efficiency of the transportation services they provide. By using EDI systems, a trucking company, for example, may easily keep track of the origin and destination of all of its shipments throughout its service region.

The format standards for EDI documents are generally loosely written so that they can satisfy a wide variety of user needs. Thus, for example, while an EDI invoice format may have well-defined data fields, several aspects of the EDI invoice are variable. As a result, trading partners who agree to use an EDI system may agree to the format of communication between them prior to conducting a business transaction, and thereafter communication between the trading partners has the potential to occur on an almost immediate basis.

Although EDI systems represent a significant improvement in business communications between trading partners, known EDI systems stand in need of improvement in document translation efficiency. A particular problem in the translation of EDI documents is the need to assure that the documents, as they are generated from various points within a trading partner, satisfy the EDI document format EDI requirements. This is particularly important in cases where failure to satisfy applicable EDI document format requirements causes the translation to be either significantly incorrect or fully prohibited. It is, therefore, important that the sending trading partner ascertain that all documents satisfy the information and format requirements of the receiving trading partner before the trading partner sends them.

Known methods of testing EDI document translations require that when a receiving trading partner encounters a transmission error, the sending partner must identify and correct the error and, then, resend a corrected test EDI document file. This process often requires numerous iterations and creates time lapses which strain productivity. Correcting translation errors using a conventional EDI editing system has not proven practical, because any adjustment in the data link of EDI transmission requires that every character following the modification be adjusted. This results in a significant amount of tedious effort between both trading partners. This type of batch processing by the recipient is further limited, because only upon the detection of an error by the recipient can action be taken to correct the problem. Once this problem is corrected, it is necessary to completely rerun the file which may be halted again as a result of yet another error later in the EDI document file translation.

As a result, in order for EDI document transmissions to reach their full potential efficiency and speed there is a need for as a method and system for rapidly increasing the data translation rate between trading partners, it is necessary to have a rapid EDI translation test facility that does not strain the productivity of the receiving trading partner.

There is a need for a method and system that eliminates the batch processing necessary to identify errors in EDI translations.

There is yet the need for a method and system that permits EDI system operators to identify and correct EDI transmission errors without the need to begin again the EDI document file translation process.

SUMMARY OF THE INVENTION

The present invention, accordingly, provides an electronic data interchange testing method and system that overcomes the problems and satisfies the needs previously considered.

According to one aspect of the invention, there is provided a method for pre-production translation testing of EDI document files that comprises the steps of generating a plurality of control displays for controlling the pre-production translation of the EDI document file. Next, translation of the file takes place until a translation error arises. The method of the present invention is to display the translation error on one of the control displays so that the error may be corrected using an input to the control display. The next step is to correct the displayed translation error as indicated by the control display. This process of translating the file until a translation error arises, displaying the translation error for correction, and correcting the translation error continues until the EDI file is fully translated.

According to another aspect of the invention, there is provided within one of the control displays a plurality of initial queries for inputting initialization data pertaining to the EDI document file. The queries relate to the particular translation configuration for translating the data into a particular application program that has the ability to use the EDI document file. Moreover, a particularly attractive aspect of the invention is its ability to produce textual segment files for containing in textual form predetermined segments of the EDI file and permitting an operator to edit the textual segment file in response to the indicated translation error. Once all errors have been noted and a translation of the relevant section is complete, the segment is stored in a working file. The working file contains all of the previously corrected segments. Through this segmented approach, the working file becomes a corrected copy of the original EDI document file. Hence, upon the complete translation of the original EDI document file, the operator has the original EDI document file and a working EDI document file that was created by the segmentation process.

A technical advantage of the present invention is that it permits EDI systems to realize their intended benefits by eliminating redundant data flows that occur in known systems when EDI document files have translation errors. The EDI test facility of the present invention provides the receiving trading partner the ability to perform pre-production translation testing of EDI document files just prior to their translation. As a result, the EDI document file is fully translated and any errors incurred during this process are logged and can be made available to the sending trading partner as advised corrections; thus minimizing unproductive time lapses and iterative communication cycles between trading partners.

Another advantage of the present invention is that it fully avoids the batch processing that was heretofore necessary in the detecting EDI transmission file errors. Using the method and system of the present invention, a trading partner may employ the EDI test facility to correct interactively EDI document file transmission errors. This allows the trading partner to perform a single EDI document file translation and therefrom produce an error-free translated EDI document file. Because only one translation operation is necessary to produce the error-free EDI document file, the present invention eliminates much of the tedious work and productivity strain presently existing in EDI document file translation.

Yet another advantage of the present invention is that it permits the integration of numerous EDI application programs for error correction and translation. The integration that the present invention provides is functionally transparent to the operator and permits EDI document file translation with any type of translator. The solution that the preferred embodiment provides permits changing the test process from one in which a number of inadequate or unrelated tools are used for EDI translation to a process where an integrated and easy to use tool kit exists to aid the EDI translation operator. As a result, the interactive testing that the preferred embodiment provides significantly reduces transmission testing cycle time. This reduces software development costs and improves overall productivity in EDI document file applications among trading partners.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention and its modes of use and advantages are best understood by reference to the following description of illustrative embodiments when read in conjunction with the accompanying drawings, wherein:

FIG. 1 through 4 are various translation screens usable in a association with the preferred embodiment;

FIG. 5 is a flow chart illustrating the operation of the EDI test facility of the preferred embodiment; and

APPENDIX A provides a listing of the software code that the preferred embodiment of the present invention implements for EDI document file translation testing.

DETAILED DESCRIPTION OF THE INVENTION

The preferred embodiment of the present invention is best understood by referring to the FIGUREs wherein like numerals are used for like and corresponding parts of the various drawings.

The EDI test facility of the preferred embodiment integrates within the EDI system environment an operator interactive translation test facility that is accessible through a computer time share option link. In this environment, the EDI test facility of the preferred embodiment has numerous test configuration options. The EDI test facility of the preferred embodiment integrates its operation with the principal communication path among EDI partners for EDI transmissions known as the EDI system gateway. This permits an EDI system operator to locate and select an EDI transmission file for immediate translation testing. Once translation testing has commenced, error situations are brought to the operator's attention along with recommendations for correcting the error. The operator has the option to fix the error and continue testing until the translator detects another translation error. As translation testing continues, the test results are saved into a working file. The working file may be tested to verify a successful translation. Additionally, the preferred embodiment generates a log file to provide the operator with a listing of errors encountered during translation testing.

The EDI test facility may be used on any computer equipped to perform EDI translations and may operate in conjunction with any commercially available EDI translator software package. Examples of translator packages usable with the preferred embodiment include the following: transettlements, interbridge and proprietary translators.

To use the EDI test facility of the preferred embodiment, the operator may enter a time sharing option and receive an EDI document file on which to perform testing. To perform the operation, the EDI test facility of the preferred embodiment presents the operator with a set of operator friendly panels. FIGS. 1–4 illustrate the panels or screens that the operator sees in testing EDI document file for translation errors. In particular, FIG. 1 illustrates the "Translator Configuration Screen" that the preferred embodiment provides to the EDI translation test operator. The Translator Configuration Screen of FIG. 1, as indicated by Translator Configuration label 10, permits the operator to input a Command for EDI translation at point 12 of the screen, the EDI translator program that the operator will use at point 14, the EDI translation plan at point 16, the EDI Steplib, at points 18 and 20, EDI parms at point 22, and at point 24 the ability to respond to a query of whether a translation identified at points 14–22 as being translated again.

The EDI Steplib input defines a library associated with the test facility wherein the translator program resides, and the EDI parms input receives the parameters that the operator desires to pass to the translator program. The operator may provide these Translator Configuration Screen inputs to the EDI test facility of the preferred embodiment using a key board or other computer input device.

Associated with each of the inputs of points 14–24 are respective parameter descriptors. In particular, for the Program input point 14, the preferred embodiment indicates at point 26 that the proper response to the program input 14 is the "Translator Name." For the EDI plan input 16, the "DB2 Plan" parameter descriptor 28 means that for this particular translator, the DB2 plan is used. For Steplib inputs 28 and 20, descriptors 30 and 32 specify that the "Full Name" of the Steplib is necessary and that no quotes may be used. Parms input 22 must be Translated Parms, as descriptor 34 indicates. The appropriate response for the "Again" input 24 is "yes" or "no" with a default to "yes" as indicated by descriptor 36.

Once the operator establishes the translator configuration by appropriately responding to the Translator Configuration Screen of FIG. 1, the operator indicates the completion of this step by hitting the enter key. Test Facility Screen of FIG. 2 appears. Immediately thereafter, identifies Test Facility label 38 the Test Facility Screen. With this screen, the operator may input a command at point 12 and set up particular files necessary to perform the EDI document file transmission testing. For example, in the preferred embodiment, the operator provides to the EDI Test Facility the input file at point 40. In this example, the input file has the name, ".AAA.EDI.I.EXPCWMRT." The operator defines a work file at point 42 (e.g., ".DAMMSBG.WORK"), a segment file at point 44 (e.g., ".DAMMSBG.SEGMENT"), and a log file (e.g., "DAMMSBG.LOG") at point 46. The Test Facility Screen also assists the operator by describing the types of fields necessary at points 40–46 by the input descriptors 48 which appear as ".(Full Name, No Quotes)."

In response to this information and a subsequent command to conduct testing that the operator inputs at point 12, the Test Facility Screen can display the existence of a translation error. FIG. 3 shows the Test Facility screen that appears during translation testing. FIG. 3 shows outputs at Segment Number designator 50 and Error Explanation output 52 to provide indication of errors. In the example, the segment number where an error exists is segment number "000003" having an associated error code of "EER14" and an explanation of "Bad Sql Return Code - 924." This means that at segment number 000003 there was a DB2 problem in the EDI document file translation. With this error identifying information, the operator may insert an "Edit" command into the Command input point 12 of the Test Facility Screen to see the Edit Screen that appears at FIG. 4.

The preferred embodiment of the present invention, upon identifying the translation error, places a segment of the original input file that contains the translation error into a segment file. The segment file, in the example of the preferred embodiment, is identified at point 44 of the Test Facility Screens of FIGS. 2 and 3 and the Edit Screen designator 54. The Edit Screen designator 54 shows that the segment file name is "DACCJBM-.SEGMENT." The Edit Label 56 indicates to the operator that the operator is viewing the Edit Screen.

In the Edit Screen, as in the Translator Configuration Screen of FIG. 1 and the Test Facility Screen of FIGS. 2 and 3, command input 12 permits the operator to provide a command input. Other outputs of the Edit Screen include descriptive output of the results of the translation at output point 58, the Standard for translation at point 60 (e.g., "ANSI") the Release descriptor at output point 62, (e.g., "00200"), the applicable Version at output point 64 (e.g., "002001"), and the particular Agency for output at point 66 (e.g., "X"). Because of the "Last Segment Process Successfully" output point 68, the operator at all times knows the last segment that was successfully processed. At the "Reason" output point 70, the operator receives the same information that previously appeared at Error Explanation output 52 of the Test Facility Screen shown in FIG. 3. This provides as the reason why the translation error occurred. Finally, the operator is prompted to "Correct Identified Errors And Hit PF3 to retranslate the corrected segment (e.g., segment 3 in this example).

The bottom part of the operator screen appearing at FIG. 4 shows the portion of the original EDI document file that the segment file contains. With this small segment, the operator may identify the error that the Test Facility Search lists and correct it. After which, the operator may depress the PF3 key of his keyboard to retranslate the segment and thereby verify that the error has been corrected.

In using the EDI Test Facility of the preferred embodiment, at each segment that the test facility identifies, the Test Facility output of FIG. 3 and the Edit Screen output of FIG. 4 communicate to the operator the existence of an error and the error location, as well as provide to the operator the ability to correct the error interactively. Once the error is corrected, the operator retranslates the corrected segment and the EDI Test Facility of the preferred embodiment continues to translate the EDI document file (e.g., DAMMKMM.FB.DATA of FIG. 3) until the translation is complete.

The Translation Incomplete signal 53 of FIG. 3 indicates that the translation of input file DAMMKMM.FBDATA is not completed because of the error identified by segment number output 50 and error explanation output 52 (i.e., "ERR14, Badsql Return Code - 924 at segment 000003).

FIG. 5 shows a flow chart of the preferred EDI Test Facility embodiment to provide to the operator the screens appearing in FIG. 1–4. First the operator fills in the Transfer Configuration Screen to establish the configuration files of step 74. Next, the operator fills in the test facility panel for input, work, segment, and log files at step 76. Also at step 76, using the Test Facility screens of FIGS. 2 and 3 the EDI Test Facility of the preferred embodiment displays any error messages arising from the EDI translation. Next, the EDI Test Facility of the preferred embodiment at step 78 permits the operator to fill in the translator configuration of FIG. 1. The preferred embodiment then translates the data at step 80 and queries whether an error has been found in the EDI file translation at step 82.

If no error occurs, the preferred embodiment sends a translation successful message to the Test Facility screen at step 84 and then permits the operator to change the input work segment and log files and continue at steps 76 and the Translator Configuration of step 78. On the other hand, if an error is found at step 82, EDI test facility of the preferred embodiment at step 86, issues the information to the Test Facility Screen (see FIG. 3) and provides the operator with the ability to use the Edit Facility of the preferred embodiment. At step 86, the preferred embodiment also logs the problem in the previously designated log file (see FIG. 3).

Under the edit facility, the EDI Test Facility permits the operator to make changes to the data at step 88 and query whether any changes were made at step 90. If no changes were made, control returns to step 76 where the operator is to fill in the input, work, segment, and log file as well as to display the error message arising from the failed translation. On the other hand, if changes are made then the program control returns to step 80 to translate data and determine whether any further error exists.

Appendix A provides a complete listing of the source code for the EDI Test Facility of the preferred embodiment.

Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope the invention as defined in the appended claims.

APPENDIX A



```
         TITLE 'EDITSBED - EDI TEST FACILITY'
         SPACE 2
*****************************************************************
*---------------------------------------------------------------*
*              -----       N O T I C E      -----               *
*       THIS EDI TEST FACILITY SOURCE MODULE                    *
*                    IS TI CLASSIFIED:                          *
* T E X A S  I N S T R U M E N T S  I N T E R N A L  D A T A   *
*   P R O P E R T Y  O F  T E X A S  I N S T R U M E N T S     *
*                         O N L Y                               *
*                TEXAS INSTRUMENTS, INC.                        *
*   13500 N. CENTRAL EXPRESSWAY, DALLAS, TEXAS   75265          *
*---------------------------------------------------------------*
*****************************************************************
         SPACE 2
         REGS
         SPACE 2
         IHASDWA
         SPACE 2
         EDIDEQU
         SPACE 2
         CVT   DSECT=YES
         TICVT
         SPACE 2
         IFGACB
         SPACE 2
         IFGRPL
         SPACE 2
         IEFZB4D0
         SPACE 2
         IEFZB4D2
         SPACE 2
         DCBD  DSORG=BS,DEVD=DA
         SPACE 2
DCBPARMS DSECT
DCBXDDNM DS    CL8
DCBXRFMT DS    X
DCBXLREC DS    XL2
DCBXBLKS DS    XL2
DCBXPRIM DS    XL3
DCBXNEW  EQU   DCBPARMS,*-DCBPARMS,C'X'
TRANREC  DSECT
TRANSTND DS    CL8
TRANRLSE DS    CL5
TRANVERS DS    CL12
TRANAGCY DS    CL2
TRANSDLM DS    CL1
TRANREAS DS    CL71
TRANBIF  DS    CL10
TRANWELM DS    CL8
TRANLAST DS    CL6
TRANTAG  DS    CL20
TRANVAL  DS    CL40
TRANSTOR EQU   TRANTAG,*-TRANTAG,C'C'
EDITSBED CSECT
         USING EDITSBED,R10           NOTE BASE ADDRESSIBILITY
         STM   R14,R12,12(R13)       SAVE ENTRY REGS
         LR    R10,R15               COPY ENTRY ADDRESS
         LA    R11,2048(,R10)        INITIALIZE 2ND BASE REG
         LA    R11,2048(,R11)

         USING EDITSBED+4096,R11
         LA    R1,SAVEAREA           POINT TO SAVE AREA
         ST    R13,4(,R1)            LINK TO CALLERS SAVE AREA
         ST    R1,8(,R13)            LINK TO OUR SAVE AREA
         LR    R13,R1                ESTABLISH SAVE AREA
         SPACE 1
*----------------------------------------------------------------------*
*        SET UP AN ESTAE EXIT                                          *
*----------------------------------------------------------------------*
         SPACE 1
         ESTAE TBABEND,              ESTABLISH AN ESTAE               +
               PARAM=(R10),                                           +
               XCTL=YES
         SPACE 1
*----------------------------------------------------------------------*
*        INITIALIZE                                                    *
```

```
*----------------------------------------------------------------------*
         SPACE 1
         OI    FLAG1,INIT           SET INITIALIZING
         USING IHADCB,R12
         SPACE 1
         LOAD  EP=ISPLINK           LOAD LINK PROGRAM
         SPACE 1
         ST    R0,ISPLADDR          SAVE ADDRESS
         SPACE 1
*----------------------------------------------------------------------*
*        DEFINE PROCESSSING OPTIONS FOR DIALOGUE SERVICE               *
*----------------------------------------------------------------------*
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(CONTROL,ERRORS,RETURN),VL
         SPACE 1
*----------------------------------------------------------------------*
*        DEFINE MISC. VARIABLE NAMES TO ISPF                           *
*----------------------------------------------------------------------*
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,ZUSERLIT,ZUSER,CHAR,LENGTH8),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNLIT,DSN,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNWLIT,DSNW,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNALITT,DSNAT,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNALITP,DSNAP,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNCLITT,DSNCT,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNCLITP,DSNCP,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNILITT,DSNIT,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNILITP,DSNIP,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNXLITT,DSNXT,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNXLITP,DSNXP,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNOLITT,DSNOT,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNOLITP,DSNOP,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNSLIT,DSNS,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DSNLLIT,DSNL,CHAR,LENGTH44),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,STDLIT,STD,CHAR,LENGTH8),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,RLSLIT,RLS,CHAR,LENGTH5),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,VERSLIT,VERS,CHAR,LENGTH12),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,AGCYLIT,AGCY,CHAR,LENGTH2),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,REASLIT,REAS,CHAR,LENGTH71),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,HUMBLIT,HUMB,CHAR,LENGTH6),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,LASTLIT,LASTSEG,CHAR,LENGTH6),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,RTC,RTNCODE,HEX,LENGTH4),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,REEZ,REEZCODE,HEX,LENGTH2),VL
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VDEFINE,DD,DDERR,CHAR,LENGTH8),VL
         SPACE 1
*-----------------------------------------------------------------*
*        CREATE TABLE NEEDED FOR FIRST PANEL                      *
*-----------------------------------------------------------------*
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(TBCREATE,VARTABLE,,VARLIST,NOWRITE),VL
         SPACE 1
         LTR   R15,R15              ERROR?
         BNZ   ERROR01              YES-
         SPACE 1
*-----------------------------------------------------------------*
*        RETRIEVE TSO USERID                                      *
*-----------------------------------------------------------------*
         SPACE 1
         L     R15,ISPLADDR         LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VGET,USERLIST,SHARED),VL
         SPACE 1
*-----------------------------------------------------------------*
*        ALLOCATE DISP=SHR DATASETS NEEDED BY TRANSLATOR          *
*-----------------------------------------------------------------*
         SPACE 1
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE
         LA    R2,DSLISTS           POINT TO DATASET LIST
         USING DCBPARMS,R2          GET ADDRESSABILITY
DSLISTSX DS    0H
         LA    R1,DSALLOCS          POINT TO TEXT UNIT LIST
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK
         CLI   0(R2),C' '           END OF LIST?
         BE    ALLOCOLD             YES-
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),DCBXDDNM SET DDNAME
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),=CL44' ' BLANK OUT DSN
         MVC   TXTDSN+S99TUPAR-S99TUNIT(L'ZUSER),ZUSER COPY TSO USERID
         LA    R15,TXTDSN+S99TUPAR-S99TUNIT POINT TO WORK AREA
         LA    R14,44               SET COUNT
FINDBLNX DS    0H
         CLI   0(R15),C' '          FIND FIRST BLANK
         BE    FOUNDBLX             FOUND IT-
         LA    R15,1(R15)           POINT TO NEXT BYTE
         BCT   R14,FINDBLNX
FOUNDBLX DS    0H
         MVC   0(4,R15),=CL4'.TF.' SET MIDDLE NODE
         LA    R15,4(R15)           INCREMENT POINTER
         MVC   0(8,R15),DCBXDDNM    SET REST OF DSN
         BAL   R9,DYNA              GO ALLOC FILE
         B     CKERRORX             ERROR ON ALLOCATION
NEXTLISS DS    0H
         LA    R2,L'DCBXNEW(R2)     POINT TO NEXT ENTRY
         B     DSLISTSX             CONTINUE
CKERRORX DS    0H
         CLC   =XL2'1708',DYNRB+S99ERROR-S99RB LOCATE ERROR?
         BNE   ERROR02              NO-
         LA    R1,DSALLOCN          POINT TO TEXT UNIT LIST
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK
         MVC   TXTRECFM+S99TUPAR-S99TUNIT(L'DCBXRFMT),DCBXRFMT
         MVC   TXTLRECL+S99TUPAR-S99TUNIT(L'DCBXLREC),DCBXLREC
         MVC   TXTBLKSZ+S99TUPAR-S99TUNIT(L'DCBXBLKS),DCBXBLKS
         MVC   TXTPRIME+S99TUPAR-S99TUNIT(L'DCBXPRIM),DCBXPRIM
         BAL   R9,DYNA              GO ALLOC FILE
         B     ERROR02              ERROR ON ALLOCATION
         B     NEXTLISS             CONTINUE
         DROP  R2
         SPACE 1
*-----------------------------------------------------------------*
*        ALLOCATE DISP=OLD DATASETS NEEDED BY TRANSLATOR          *
*-----------------------------------------------------------------*
         SPACE 1
ALLOCOLD DS    0H
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE
         LA    R2,DSLISTO           POINT TO DATASET LIST

         USING DCBPARMS,R2          GET ADDRESSABILITY
DSLISTOX DS    0H
         LA    R1,DSALLOCO          POINT TO TEXT UNIT LIST
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK
         CLI   0(R2),C' '           END OF LIST?
         BE    ALLOCSO              YES-
         MVC   TXTDD+S99TUPAR-S99TUNIT(8).DCBXDDNM SET DDNAME
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),=CL44' ' BLANK OUT DSN
         MVC   TXTDSN+S99TUPAR-S99TUNIT(L'ZUSER),ZUSER COPY TSO USERID
         LA    R15,TXTDSN+S99TUPAR-S99TUNIT POINT TO WORK AREA
         LA    R14,44               SET COUNT
FINDBLNK DS    0H
         CLI   0(R15),C' '          FIND FIRST BLANK
         BE    FOUNDBLK             FOUND IT-
         LA    R15,1(R15)           POINT TO NEXT BYTE
         BCT   R14,FINDBLNK
FOUNDBLK DS    0H
         MVC   0(4,R15),=CL4'.TF.' SET MIDDLE NODE
```

```
          LA    R15,4(R15)              INCREMENT POINTER               02590000
          MVC   0(8,R15),DCBXDDNM       SET REST OF DSN                 02600000
          BAL   R9,DYNA                 GO ALLOC FILE                   02610000
          B     CKERROR                 ERROR ON ALLOCATION             02620000
NEXTLISO  DS    0H                                                      02630000
          LA    R2,L'DCBXNEW(R2)        POINT TO NEXT ENTRY             02640000
          B     DSLISIOX                CONTINUE                        02650000
CKERROR   DS    0H                                                      02660000
          CLC   =XL2'1708',DYNRB+S99ERROR-S99RB LOCATE ERROR?           02670000
          BNE   ERROR02                 NO-                             02680000
          LA    R1,DSALLOCN             POINT TO TEXT UNIT LIST         02690000
          ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK    02700000
          MVC   TXTRECFM+S99TUPAR-S99TUNIT(L'DCBXRFMT),DCBXRFMT         02710000
          MVC   TXTLRECL+S99TUPAR-S99TUNIT(L'DCBXLREC),DCBXLREC         02720000
          MVC   TXTBLKSZ+S99TUPAR-S99TUNIT(L'DCBXBLKS),DCBXBLKS         02730000
          MVC   TXTPRIME+S99TUPAR-S99TUNIT(L'DCBXPRIM),DCBXPRIM         02740000
          BAL   R9,DYNA                 GO ALLOC FILE                   02750000
          B     ERROR02                 ERROR ON ALLOCATION             02760000
          B     NEXTLISO                CONTINUE                        02770000
          DROP  R2                                                      02780000
          SPACE 1                                                       02790000
*---------------------------------------------------------------------* 02800000
*         ALLOCATE SYSOUT NEEDED BY TRANSLATOR                        * 02810000
*---------------------------------------------------------------------* 02820000
          SPACE 1                                                       02830000
ALLOCSO   DS    0H                                                      02840000
          LA    R1,SOALLOC              POINT TO TEXT UNIT LIST         02850000
          ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK    02860000
          MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE            02870000
          LA    R2,SOLIST               POINT TO SYSOUT LIST            02880000
SOLISTX   DS    0H                                                      02890000
          CLI   0(R2),C' '              END OF LIST?                    02900000
          BE    GETVARS                 YES-                            02910000
          MVC   TXTDD+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME            02920000
          BAL   R9,DYNA                 GO ALLOC DATABASE               02930000
          B     ERROR02                 ERROR ON ALLOCATION             02940000
          LA    R2,8(R2)                POINT TO NEXT DDNAME            02950000
          B     SOLISTX                 CONTINUE                        02960000
          SPACE 1                                                       02970000
*---------------------------------------------------------------------* 02980000
*         RETRIEVE PANEL VARIABLES FOR DISPLAY                        * 02990000
*---------------------------------------------------------------------* 03000000
          SPACE 1                                                       03010000
GETVARS   DS    0H                                                      03020000
          L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE 03030000
          CALL  (15),(VGET,SAVLIST,PROFILE),VL                          03040000
          SPACE 1                                                       03050000
*---------------------------------------------------------------------* 03060000
*         DISPLAY CONFIGURATION PANEL TO GET FILE NAMES               * 03070000
*---------------------------------------------------------------------* 03080000
          SPACE 1                                                       03090000
CONFIG    DS    0H                                                      03100000
          LA    R1,DSUNCONC             POINT TO TEXT UNIT LIST         03110000
          ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK    03120000
          MVI   DYNRB+S99VERB-S99RB,S99VRBDC SET TO UNALLOCATE          03130000
          LA    R2,DSLIST               POINT TO DS LIST                03140000
UNCONC    DS    0H                                                      03150000
          CLC   =C'VSAM',0(R2)          END OF LIST?                    03160000
          BE    UNALCONF                YES-                            03170000
          MVC   TXTDDU+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME           03180000
          BAL   R9,DYNA                 GO UNCONCAT FILES               03190000
          B     *+4                     ERROR ON UNCONCAT               03200000
          LA    R2,104(R2)              POINT TO NEXT DDNAME            03210000
          B     UNCONC                  CONTINUE                        03220000
UNALCONF  DS    0H                                                      03230000
          LA    R1,DSUNALOC             POINT TO TEXT UNIT LIST         03240000
          ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK    03250000
          MVI   DYNRB+S99VERB-S99RB,S99VRBUN SET TO UNALLOCATE          03260000
          LA    R2,DSLIST               POINT TO DS LIST                03270000
UNALDSX   DS    0H                                                      03280000
          CLI   0(R2),C' '              END OF LIST?                    03290000
          BE    DISPCONF                YES-                            03300000
          MVC   TXTDD+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME            03310000
          BAL   R9,DYNA                 GO UNALLOCATE FILE              03320000
          B     *+4                     ERROR ON UNALLOCATION           03330000
          LA    R2,52(R2)               POINT TO NEXT DDNAME            03340000
          B     UNALDSX                 CONTINUE                        03350000
          SPACE 1                                                       03360000
DISPCONF  DS    0H                                                      03370000
          L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE 03380000
          CALL  (15),(DISPLAY,PANEL3),VL DISPLAY                        03390000
          SPACE 1                                                       03400000
          CH    R15,=H'8'               END/RETURN ENTERED?             03410000
          BE    ENDSESS                 YES-                            03420000
          NI    FLAG1,FF-INIT           RESET INIT FLAG                 03430000
          SPACE 1                                                       03440000
*---------------------------------------------------------------------* 03450000
*         ALLOCATE DISP=SHR DATASETS NEEDED BY TRANSLATOR             * 03460000
*---------------------------------------------------------------------* 03470000
```

```
         SPACE 1                                                        03480000
         LA    R1,DSALLOCS            POINT TO TEXT UNIT LIST           03490000
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK     03500000
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE             03510000
         LA    R2,DSLIST              POINT TO DATASET LIST             03520000
DSLISTX  DS    0H                                                       03530000
         CLI   0(R2),C' '             END OF LIST?                      03540000
         BE    CONCLIST               YES-                              03550000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME             03560000
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),8(R2) COPY DS NAME          03570000
         BAL   R9,DYNA                GO ALLOC FILE                     03580000
         B     ERROR02                ERROR ON ALLOCATION               03590000
         LA    R2,52(R2)              POINT TO NEXT DATASET NAME        03600000
         B     DSLISTX                CONTINUE                          03610000
CONCLIST DS    0H                                                       03620000
         LA    R1,DSCONCLS            POINT TO TEXT UNIT LIST           03630000
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK     03640000
         MVI   DYNRB+S99VERB-S99RB,S99VRBCC SET TO ALLOCATE             03650000
         LA    R2,DSLIST              POINT TO DATASET LIST             03660000
CONCNEXT DS    0H                                                       03670000
         CLC   =C'VSAM',0(R2)         END OF LIST?                      03680000
         BE    DISPPRIM               YES-                              03690000
         MVC   TXTCONC+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME           03700000
         LA    R2,52(R2)              POINT TO NEXT DDNAME              03710000
         MVC   TXTCONCX,0(R2)         COPY SECOND DDNAME                03720000
         BAL   R9,DYNA                GO ALLOC FILE                     03730000
         B     ERROR02                ERROR ON ALLOCATION               03740000
         LA    R2,52(R2)              POINT TO NEXT DDNAME              03750000
         B     CONCNEXT               CONTINUE                          03760000
         SPACE 1                                                        03770000
*---------------------------------------------------------------------* 03780000
*        DISPLAY PRIMARY PANEL                                        * 03790000
*---------------------------------------------------------------------* 03800000
         SPACE 1                                                        03810000
DISPPRIM DS    0H                                                       03820000
         LA    R12,LOGDCB               POINT TO LOG DCB                03830000
         TM    DCBOFLGS,DCBOFOPN        IS IT OPEN?                     03840000
         BNO   LOGCLOSE                 NO-                             03850000
         SPACE 1                                                        03860000
         CLOSE ((R12))                  CLOSE IT                        03870000
         SPACE 1                                                        03880000
         LR    R1,R12                   COPY DCB ADDRESS                03890000
         SPACE 1                                                        03900000
         FREEPOOL (1)                   FREE QSAM BUFFERS               03910000
LOGCLOSE DS    0H                                                       03920000
         LA    R1,DSUNALOC            POINT TO TEXT UNIT LIST           03930000
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK     03940000
         MVI   DYNRB+S99VERB-S99RB,S99VRBUN SET TO UNALLOCATE           03950000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'USERFILE'                03960000
         BAL   R9,DYNA                GO UNALLOC                        03970000
         B     *+4                    ERROR ON UNALLOCATION             03980000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'INPUT'                   03990000
         BAL   R9,DYNA                GO UNALLOC                        04000000
         B     *+4                    ERROR ON UNALLOCATION             04010000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'SGMTFILE'                04020000
         BAL   R9,DYNA                GO UNALLOC                        04030000
         B     *+4                    ERROR ON UNALLOCATION             04040000
         SPACE 1                                                        04050000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'LOG'                     04060000
         BAL   R9,DYNA                GO UNALLOC                        04070000
         B     *+4                    ERROR ON UNALLOCATION             04080000
         SPACE 1                                                        04090000
         L     R15,ISPLADDR           LOAD ADDRESS OF ISPLINK ROUTINE   04100000
         CALL  (15),(TBTOP,VARTABLE),VL DISPLAY                         04110000
         SPACE 1                                                        04120000
         L     R15,ISPLADDR           LOAD ADDRESS OF ISPLINK ROUTINE   04130000
         CALL  (15),(TBDISPL,VARTABLE,PRIMARY),VL DISPLAY               04140000
         SPACE 1                                                        04150000
         CH    R15,=H'8'              END/RETURN ENTERED?               04160000
         BE    CONFIG                 YES-                              04170000
         SPACE 2                                                        04180000
*-----------------------------------------------------------*           04190000
*        DELETE AND RECREATE TABLE OF ERRORS                *           04200000
*-----------------------------------------------------------*           04210000
         SPACE 2                                                        04220000
         L     R15,ISPLADDR           LOAD ADDRESS OF ISPLINK ROUTINE   04230000
         CALL  (15),(TBCLOSE,VARTABLE),VL                               04240000
         SPACE 1                                                        04250000
         L     R15,ISPLADDR           LOAD ADDRESS OF ISPLINK ROUTINE   04260000
         CALL  (15),(TBCREATE,VARTABLE,,VARLIST,NOWRITE),VL             04270000
         SPACE 1                                                        04280000
         LTR   R15,R15                ERROR?                            04290000
         BNZ   ERROR01                YES-                              04300000
         SPACE 2                                                        04310000
*-----------------------------------------------------------*           04320000
*        ALLOCATE INPUT FILE SPECIFIED BY USER              *           04330000
*-----------------------------------------------------------*           04340000
         SPACE 2                                                        04350000
         LA    R1,DSALLOCS            POINT TO TEXT UNIT LIST           04360000
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK     04370000
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE             04380000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'USERFILE' SET DDNAME  04390000
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),DSN   COPY DS NAME       04400000
         BAL   R9,DYNA                GO ALLOC FILE                  04410000
         B     ERROR02                ERROR ON ALLOCATION            04420000
         SPACE 1                                                     04430000
         LA    R1,DSALLOC0            POINT TO TEXT UNIT LIST        04440000
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK  04450000
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE          04460000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'LOG' SET DDNAME       04470000
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),DSNL  COPY DS NAME       04480000
         BAL   R9,DYNA                GO ALLOC FILE                  04490000
         B     ERROR02                ERROR ON ALLOCATION            04500000
         LA    R1,DSALLOC0            POINT TO TEXT UNIT LIST        04510000
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK  04520000
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE          04530000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'INPUT' SET DDNAME     04540000
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),DSNW  COPY DS NAME       04550000
         BAL   R9,DYNA                GO ALLOC FILE                  04560000
         B     ERROR02                ERROR ON ALLOCATION            04570000
         LA    R12,INPDCB             POINT TO DCB                   04580000
         MVC   DDERR,DCBDDNAM         SET DDNAME IN ERROR MSG        04590000
         SPACE 1 -                                                   04600000
         OPEN  ((R12),(INPUT))        OPEN FILE                      04610000
         SPACE 1                                                     04620000
         TM    DCBOFLGS,DCBOFOPN      WAS OPEN SUCCESSFUL?           04630000
         BNO   ERROR06                NO-                            04640000
         TM    DCBRECFM,DCBRECF+DCBRECBR FB RECORDS?                 04650000
         BNO   ERROR10                ERROR                          04660000
         LH    R0,DCBLRECL            GET LRECL                      04670000
         CH    R0,=H'80'              LRECL = 80?                    04680000
         BNE   ERROR10                NO ERROR                       04690000
         SPACE 1                                                     04700000
         CLOSE ((R12))                CLOSE FILE                     04710000
         SPACE 1                                                     04720000
         MVI   DYNRB+S99VERB-S99RB,S99VRBAL SET TO ALLOCATE          04730000
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),=CL8'SGMTFILE' SET DDNAME  04740000
         MVC   TXTDSN+S99TUPAR-S99TUNIT(44),DSNS  COPY DS NAME       04750000
         BAL   R9,DYNA                GO ALLOC FILE                  04760000
         B     ERROR02                ERROR ON ALLOCATION            04770000
         LA    R12,OUTDCBX            POINT TO DCB                   04780000
         MVC   DDERR,DCBDDNAM         SET DDNAME IN ERROR MSG        04790000
         SPACE 1                                                     04800000
         OPEN  ((R12),(INPUT))        OPEN FILE                      04810000
         SPACE 1                                                     04820000
         TM    DCBOFLGS,DCBOFOPN      WAS OPEN SUCCESSFUL?           04830000
         BNO   ERROR06                NO-                            04840000
         TM    DCBRECFM,DCBRECV+DCBRECBR VB RECORDS?                 04850000
         BNO   ERROR11                NO- ERROR                      04860000
         LH    R0,DCBLRECL            GET LRECL                      04870000
         CH    R0,=H'259'             LRECL = 259?                   04880000
         BNE   ERROR11                NO ERROR                       04890000
         SPACE 1                                                     04900000
         CLOSE ((R12))                CLOSE FILE                     04910000
         SPACE 1                                                     04920000
         MVC   IDCB,=CL8'USERFILE' SET INPUT DDNAME FOR REBLOCK      04930000
         MVC   ODCB,=CL8'INPUT' SET OUTPUT DDNAME FOR REBLOCK        04940000
         LA    R12,LOGDCB               POINT TO STORE DCB           04950000
         MVC   DDERR,DCBDDNAM           SET DDNAME IN ERROR MSG      04960000
         SPACE 1                                                     04970000
         OPEN  ((R12),(OUTPUT))         OPEN FILE                    04980000
         SPACE 1                                                     04990000
         TM    DCBOFLGS,DCBOFOPN        WAS OPEN SUCCESSFUL?         05000000
         BNO   ERROR06                  NO-                          05010000
TRANLOOP DS    0H                                                    05020000
         SPACE 1                                                     05030000
         CALL  REBLK,(DCBNAMES),VL GO REBLOCK FILE FOR XLATOR        05040000
         SPACE 1                                                     05050000
         LTR   R15,R15                  REBLOCK OK?                  05060000
         BNZ   ERROR04                  NO-                          05070000
         SPACE 1                                                     05080000
         L     R15,ISPLADDR             LOAD ADDRESS OF ISPLINK ROUTINE 05090000
         SPACE 1                                                     05100000
         CALL  (15),(SELECT,LENGTH11,SELCMD),VL                      05110000
         SPACE 1                                                     05120000
         LTR   R15,R15                  BYPASS CHECK                 05130000
         BNZ   BYPASST                  YES-                         05140000
         SPACE 1                                                     05150000
*--------------------------------------------------------------------* 05160000
*        GET INFORMATION ABOUT PROBLEM                                * 05170000
*--------------------------------------------------------------------* 05180000
         SPACE 1                                                     05190000
CHECKERR DS    0H                                                    05200000
         LA    R12,ERRDCB               POINT TO ERROR DCB           05210000
         MVC   DDERR,DCBDDNAM           SET DDNAME IN ERROR MSG      05220000
         LA    R0,BYPASST               SET EOD ADDRESS              05230000
         STCM  R0,B'0111',DCBEODA       IN DCB                       05240000
         SPACE 1                                                     05250000
         OPEN  ((R12),(INPUT))          OPEN FILE                    05260000
         SPACE 1                                                     05270000
         TM    DCBOFLGS,DCBOFOPN        WAS OPEN SUCCESSFUL?         05280000
         BNO   ERROR06                  NO-                          05290000
         L     R0,BUFFER                GET BUFFER ADDRESS           05300000
         SPACE 1                                                         05310000
         GET   ERRDCB                  RETRIEVE ERROR RECORD             05320000
         SPACE 1                                                         05330000
         CLOSE ((R12))                 CLOSE FILE                        05340000
         SPACE 1                                                         05350000
         LR    R1,R12                  COPY DCB ADDRESS                  05360000
         SPACE 1                                                         05370000
         FREEPOOL (1)                  FREE QSAM BUFFERS                 05380000
         SPACE 1                                                         05390000
         L     R6,BUFFER               GET ERROR BUFFER ADDRESS          05400000
         AH    R6,=H'4'                POINT PAST RDW                    05410000
         USING TRANREC,R6              GET ADDRESSABILITY                05420000
         MVC   STD,TRANSTND            SET STANDARD                      05430000
         MVC   RLS,TRANRLSE            SET RELEASE                       05440000
         MVC   VERS,TRANVERS           SET VERSION                       05450000
         MVC   AGCY,TRANAGCY           SET AGENCY                        05460000
         MVC   REAS,TRANREAS           SET REASON                        05470000
         MVC   LASTSEG,TRANLAST        SET LAST SEGMENT PROCESSED        05480000
         PACK  DBLWORD,TRANLAST        PACK LAST SEGMENT FIELD           05490000
         AP    DBLWORD,=P'1'           ADD ONE TO GET PROBLEM SGMT       05500000
         UNPK  NUMB,DBLWORD            GET IT BACK TO EBCDIC             05510000
         OI    NUMB+5,X'F0'            SET ZONE                          05520000
         MVC   SEP,TRANSDLM            SET SEGMENT DELIMETER             05530000
         SPACE 1                                                         05540000
*----------------------------------------------------------------------* 05550000
*        UPDATE LOG                                                    * 05560000
*----------------------------------------------------------------------* 05570000
         SPACE 1                                                         05580000
         L     R2,BUFFER               GET BUFFER ADDRESS                05590000
         MVC   0(80,R2),=CL80' '       BLANK OUT BUFFER                  05600000
         MVC   0(L'REAS,R2),REAS       COPY INTO BUFFER                  05610000
         SPACE 1                                                         05620000
         PUT   LOGDCB,(R2)             WRITE RECORD                      05630000
         SPACE 1                                                         05640000
*----------------------------------------------------------------------* 05650000
*        ADD REASON TO TABLE                                           * 05660000
*----------------------------------------------------------------------* 05670000
         SPACE 1                                                         05680000
         L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE   05690000
         CALL  (15),(TBADD,VARTABLE),VL                                  05700000
         SPACE 1                                                         05710000
         LTR   R15,R15                 ERROR?                            05720000
         BNZ   ERROR07                 YES-                              05730000
         SPACE 1                                                         05740000
*----------------------------------------------------------------------* 05750000
*        BUILD STORE FILE                                              * 05760000
*----------------------------------------------------------------------* 05770000
         SPACE 1                                                         05780000
         LA    R12,STOREDCB            POINT TO STORE DCB                05790000
         MVC   DDERR,DCBDDNAM          SET DDNAME IN ERROR MSG           05800000
         SPACE 1                                                         05810000
         OPEN  ((R12),(OUTPUT))        OPEN FILE                         05820000
         SPACE 1                                                         05830000
         TM    DCBOFLGS,DCBOFOPN       WAS OPEN SUCCESSFUL?              05840000
         BNO   ERROR06                 NO-                               05850000
         L     R2,BUFFER               GET BUFFER ADDRESS                05860000
         MVC   0(80,R2),=CL80' '       BLANK OUT BUFFER                  05870000
         LA    R6,TRANSTOR             POINT TO TAG                      05880000
         USING TRANSTOR,R6             GET ADDRESSABILITY                05890000
STORCONT DS    0H                                                        05900000
         CLC   TRANTAG(L'BEDZERO),BEDZERO END OF VALUES?                 05910000
         BE    STORQUIT                YES-                              05920000
         MVC   0(L'TRANSTOR,R2),TRANSTOR COPY INTO BUFFER                05930000
         SPACE 1                                                         05940000
         PUT   STOREDCB,(R2)           WRITE RECORD                      05950000
         SPACE 1                                                         05960000
         LA    R6,L'TRANSTOR(R6)       INCREMENT POINTER                 05970000
         B     STORCONT                CONTINUE                          05980000
STORQUIT DS    0H                                                        05990000
         CLOSE ((R12))                 CLOSE IT                          06000000
         SPACE 1                                                         06010000
         LR    R1,R12                  COPY DCB ADDRESS                  06020000
         SPACE 1                                                         06030000
         FREEPOOL (1)                  FREE QSAM BUFFERS                 06040000
         SPACE 1                                                         06050000
*----------------------------------------------------------------------* 06060000
*        OPEN INPUT FILE                                               * 06070000
*----------------------------------------------------------------------* 06080000
         SPACE 1                                                         06090000
         LA    R12,INPDCB              POINT TO INPUT DCB                06100000
         MVC   DDERR,DCBDDNAM          SET DDNAME IN ERROR MSG           06110000
         SPACE 1                                                         06120000
         OPEN  ((R12),(INPUT))         OPEN FILE                         06130000
         SPACE 1                                                         06140000
         TM    DCBOFLGS,DCBOFOPN       WAS OPEN SUCCESSFUL?              06150000
         BNO   ERROR06                 NO-                               06160000
         SPACE 1                                                         06170000
*----------------------------------------------------------------------* 06180000
*        OPEN TEMPORARY FILE FOR OUTPUT                                * 06190000
*----------------------------------------------------------------------* 06200000
```

```
         SPACE 1
         LA    R12,OUTDCB            POINT TO OUTPUT DCB
         MVC   DDERR,DCBDDNAM        SET DDNAME IN ERROR MSG
         SPACE 1
         OPEN  ((R12),(OUTPUT))      OPEN FILE
         SPACE 1
         TM    DCBOFLGS,DCBOFOPN     WAS OPEN SUCCESSFUL?
         BNO   ERROR06               NO-
         NI    BEDFLAG1,FF-INEOF-PERMIERR RESET FLAGS
NEXTSGMT DS    0H
         BAL   R9,FINDSGMT           YES- GO FIND SEGMENT
         B     ERROR08               ERROR-
         B     CLOSEOUT              EOF-
         L     R0,BUFFRDW            POINT TO SEGMENT
         SPACE 1
         PUT   OUTDCB                WRITE IT
         SPACE 1
         B     NEXTSGMT              NORMAL
CLOSEOUT DS    0H
         LA    R12,OUTDCB            POINT TO OUTPUT DCB
         SPACE 1
         CLOSE ((R12))               CLOSE IT
         SPACE 1
         LR    R1,R12                COPY DCB ADDRESS
         SPACE 1
         FREEPOOL (1)                FREE QSAM BUFFERS
         SPACE 1
*---------------------------------------------------------------------*
*        BRING UP EDIT FACILITY FOR INPUT FILE                        *
*---------------------------------------------------------------------*
         SPACE 1
EDITSGMT DS    0H
         MVC   TDSN,DSNS             SET SEGMENT FILE NAME?
         LA    R1,TDSN               POINT TO DSN
         B     *+8
IDSNLOOP DS    0H
         LA    R1,1(R1)              POINT TO NEXT BYTE
         CLI   0(R1),C' '            IS THIS A BLANK DELIMETER
         BNE   IDSNLOOP              NO- CONTINUE
         MVI   0(R1),C'*'            MOVE IN ASTERISK
SKIPTDLM DS    0H
         L     R15,ISPLADDR          LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(EDIT,TEMPDSN,,,PANEL2),VL
         SPACE 1
         CH    R15,=H'4'             ABNORMAL RETURN?
         BH    ERROR09               YES-
         BE    BYPASSX               NORMAL RETURN(NOSAVE)
         MVC   IDCB,=CL8'SGMTFILE'   SET INPUT DDNAME FOR REBLOCK
         B     TRANLOOP               GO TRANSLATE AGAIN
BYPASST  DS    0H
         SPACE 1
         CLOSE ((R12))                CLOSE FILE
         SPACE 1
         LR    R1,R12                 COPY DCB ADDRESS
         SPACE 1
         FREEPOOL (1)                 FREE QSAM BUFFERS
         SPACE 1
         MVC   MSGID,=CL8'EDIL050'    SET MSGID
         BAL   R9,SETMSGX             DISPLAY MSG
         B     DISPPRIM               DISPLAY RESULTS
BYPASSX  DS    0H
         MVC   MSGID,=CL8'EDIL063'    SET MSGID
         BAL   R9,SETMSGX             DISPLAY MSG
         B     DISPPRIM               DISPLAY RESULTS
         SPACE 1
*---------------------------------------------------------------------*
*        UNALLOCATE ALL FILES USED                                    *
*---------------------------------------------------------------------*
         SPACE 1
ENDSESS  DS    0H
         ESTAE 0                      CANCEL ESTAE
         SPACE 1
         LA    R1,DSUNALOC            POINT TO TEXT UNIT LIST
         ST    R1,DYNRB+S99TXTPP-S99RB STORE ADDRESS IN REQUEST BLK
         MVI   DYNRB+S99VERB-S99RB,S99VRBUN SET TO UNALLOCATE
         LA    R2,SOLIST              POINT TO SYSOUT LIST
UNALSYSO DS    0H
         CLI   0(R2),C' '             END OF LIST?
         BE    UNALDSO                YES-
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME
         BAL   R9,DYNA                GO UNALLOC
         B     *+4                    ERROR ON UNALLOCATION
         LA    R2,8(R2)               POINT TO NEXT DDNAME
         B     UNALSYSO               CONTINUE
UNALDSO  DS    0H
         LA    R2,DSLISTO             POINT TO DS LIST
UNALDSXO DS    0H
         CLI   0(R2),C' '             END OF LIST?
         BE    UNALDSS                YES-
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME
         BAL   R9,DYNA                GO UNALLOCATE FILE
         B     *+4                     ERROR ON UNALLOCATION
         LA    R2,L'DCBXNEW(R2)        POINT TO NEXT DDNAME
         B     UNALDSXG                CONTINUE
         SPACE 1
UNALDSS  DS    0H
         LA    R2,DSLISTS              POINT TO DS LIST
UNALDSXS DS    0H
         CLI   0(R2),C' '              END OF LIST?
         BE    CLOSTABL                YES-
         MVC   TXTDD+S99TUPAR-S99TUNIT(8),0(R2) COPY DDNAME
         BAL   R9,DYNA                 GO UNALLOCATE FILE
         B     *+4                     ERROR ON UNALLOCATION
         LA    R2,L'DCBXNEW(R2)        POINT TO NEXT DDNAME
         B     UNALDSXS                CONTINUE
         SPACE 1
CLOSTABL DS    0H
         L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(TBCLOSE,VARTABLE),VL
         SPACE 1
         L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(VPUT,SAVLIST,PROFILE),VL
         SPACE 1
*---------------------------------------------------------------------*
*        RESTORE REGISTERS AND RETURN TO CALLER                       *
*---------------------------------------------------------------------*
         SPACE 1
RETURNX  DS    0H
         L     R13,4(,R13)             RESTORE CALLERS SAVE AREA
         L     R14,12(,R13)                      RETURN ADDRESS
         LM    R0,R12,20(R13)                    REGISTERS
         BR    R14
         SPACE 1
*---------------------------------------------------------------------*
*        THIS SUBROUTINE WILL UN/ALLOCATE THE FILES NEEDED.           *
*        RETURN TO THE CALLER WITH A DISPLACEMENT DEPENDING ON        *
*        THE RETURN CODE IN R15.                                      *
*                                                                     *
*        ON ENTRY: R9 => RETURN ADDRESS                               *
*                                                                     *
*        RETURNS : 0(R9) => ERROR RETURN                              *
*                  4(R9) => NORMAL RETURN                             *
*                                                                     *
*---------------------------------------------------------------------*
         SPACE 1
DYNA     DS    0H
         LA    R1,DYNRBP               SET UP REQUEST BLOCK CHAIN
         SPACE 1
         DYNALLOC ,                    GO ALLOCATE IT
         SPACE 1
         LTR   R15,R15                 ALLOCATION SUCCESSFUL?
         BNZ   0(R9)                   NO- TAKE EXIT RETURN
         B     4(R9)                   TAKE NORMAL RETURN
         SPACE 1
*---------------------------------------------------------------------*
*        LOG MESSAGES                                                 *
*---------------------------------------------------------------------*
         SPACE 1
LOGIT    DS    0H
         L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(LOG,MSGID),VL     LOG IT
         SPACE 1
         BR    R9                      RETURN
         SPACE 1
*---------------------------------------------------------------------*
*        SET MESSAGES                                                 *
*---------------------------------------------------------------------*
         SPACE 1
SETMSGX  DS    0H
         L     R15,ISPLADDR            LOAD ADDRESS OF ISPLINK ROUTINE
         CALL  (15),(SETMSG,MSGID),VL  LOG IT
         SPACE 1
         BR    R9                      RETURN
         SPACE 1
*---------------------------------------------------------------------*
*        ERROR ROUTINES                                               *
*---------------------------------------------------------------------*
         SPACE 1
ERROR01  DS    0H                      TABLE_CREATE_ERROR
         ST    R15,RTNCODE             SAVE RETURN CODE
         MVC   MSGID,=CL8'EDIL051'     SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR02  DS    0H                      ALLOCATION FAILURE
         ST    R15,RTNCODE             SAVE RETURN CODE
         MVC   REEZCODE,DYNRB+S99ERROR-S99RB SET REASON CODE
         MVC   DDERR,TXTDD+S99TUPAR-S99TUNIT SET DDNAME IN MSG
         MVC   MSGID,=CL8'EDIL052'     SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR03  DS    0H                      ALLOCATION_FAILURE
         ST    R15,RTNCODE             SAVE RETURN CODE
         MVC   REEZCODE.DYNRB+S99ERROR-S99RB SET REASON CODE
         MVC   DDERR.TXTDD+S99TUPAR-S99TUNIT SET DDNAME IN MSG
         MVC   MSGID,=CL8'EDIL053' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR04  DS    0H                  REBLOCK ERROR
         ST    R15,RTNCODE         SAVE RETURN CODE
         MVC   MSGID,=CL8'EDIL054' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR05  DS    0H                  ATTACH FAILURE
         ST    R15,RTNCODE         SAVE RETURN CODE
         MVC   MSGID,=CL8'EDIL055' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR06  DS    0H                  OPEN FAILURE
         MVC   MSGID,=CL8'EDIL056' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR07  DS    0H                  TBADD FAILURE
         ST    R15,RTNCODE         SAVE RETURN CODE
         MVC   MSGID,=CL8'EDIL057' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR08  DS    0H                  PARSE SEGMENT
         LA    R12,INPDCB          POINT TO INPUTDCB
         SPACE 1
         CLOSE ((R12))               CLOSE IT
         SPACE 1
         LR    R1,R12                COPY DC3 ADDRESS
         SPACE 1
         FREEPOOL (1)                FREE QSAM BUFFERS
         SPACE 1
         LA    R12,OUTDCB            POINT TO OUTPUT DCB
         SPACE 1
         CLOSE ((R12))               CLOSE IT
         SPACE 1
         LR    R1,R12                COPY DCB ADDRESS
         SPACE 1
         FREEPOOL (1)                FREE QSAM BUFFERS
         SPACE 1
         MVC   MSGID,=CL8'EDIL058' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR09  DS    0H                  EDIT ERROR
         ST    R15.RTNCODE         SAVE RETURN CODE
         MVC   MSGID,=CL8'EDIL059' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR10  DS    0H                  WORK FILE FORMAT ERROR
         CLOSE ((R12))             CLOSE FILE
         SPACE 1
         MVC   MSGID,=CL8'EDIL060' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR11  DS    0H                  SEGMENT FILE FORMAT ERROR
         SPACE 1
         CLOSE ((R12))             CLOSE FILE
         SPACE 1
         MVC   MSGID,=CL8'EDIL061' SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR12  DS    0H                  SYSTEM ABEND
         MVC   MSGID,=CL8'EDIL062! SET MSG ID FAILURE
         B     ERROR
         SPACE 1
ERROR    DS    0H                  EDIT ERROR
         BAL   R9,LOGIT            GO LOG IT
         BAL   R9,SETMSGX          GO DISPLAY MSG
         TM    FLAG1,INIT          ARE WE INITIALIZING?
         BO    ENDSESS             YES- END SESSION
         B     DISPPRIM            NO- DISPLAY PANEL
         SPACE 1
*----------------------------------------------------------------------*
*                                                                      *
*        THE FOLLOWING ROUTINE RETRIEVES THE NEXT LOGICAL RECORD       *
*        FROM A DASD DATASET.                                          *
*                                                                      *
*        INPUTS:                                                       *
*                                                                      *
*        R5 -  RETURN ADDRESS                                          *
*                                                                      *
*        OUTPUTS:                                                      *
*                                                                      *
*        R0  - INPUT RECORD LENGTH                                     *
*        R1  - INPUT RECORD ADDRESS                                    *
*                                                                      *
*----------------------------------------------------------------------*
         SPACE 2
READFILE DS    0H                  ENTRY POINT IDENTIFIER
         STM   R14,R1,SAVEREGS     SAVE REGISTERS
         LA    R12,INPDCB
         TM    BEDFLAG1,INEOF+PERMIERR  EOF PREVIOUSLY REACHED?          08950000
         BC    NALLOFF,READEOF      YES-                                 08960000
         LA    R0,READEOF           POINT TO EOF EXIT ROUTINE            08970000
         STCM  R0,B'0111',DCBEODA   SAVE EODAD ADDR                      08980000
         LA    R0,READSYN           POINT TO SYNAD EXIT ROUTINE          08990000
         STCM  R0,B'0111',DCBSYNA   SAVE SYNAD ADDRESS                   09000000
         SPACE 1                                                         09010000
         GET   INPDCB               RETRIEVE NEXT RECORD                 09020000
         SPACE 1                                                         09030000
         TM    DCBRECFM,DCBRECU     RECFM U?                             09040000
         BC    ALLON,RECU           YES-                                 09050000
         TM    DCBRECFM,DC3RECV     RECFM V?                             09060000
         BC    ALLON,RECV           YES-                                 09070000
         SPACE 1                                                         09080000
*        UNDEFINED OR FIXED LENGTH RECORD FORMAT                         09090000
         SPACE 1                                                         09100000
RECU     DS    0H                                                        09110000
         LH    R0,DCBLRECL          LOAD RECORD LENGTH READ              09120000
         LTR   R0,R0                UNBLOCKED RECORDS?                   09130000
         BC    NZERO,READF200       NO-                                  09140000
         LH    R0,DCBBLKSI          RETRIEVE BLOCKSIZE                   09150000
         B     READF200             RETURN                               09160000
         SPACE 1                                                         09170000
*        VARIABLE LENGTH RECORD FORMAT                                   09180000
         SPACE 1                                                         09190000
RECV     DS    0H                                                        09200000
         LH    R0,0(,R1)            RETRIEVE VARIABLE RECORD LENGTH      09210000
         LA    R1,4(,R1)            POINT TO DATA PORTION OF RECORD      09220000
         S     R0,=F'4'             ADJUST LENGTH FOR RDW                09230000
         B     READF200             RETURN                               09240000
READEOF  DS    0H                                                        09250000
         SLR   R0,R0                CLEAR READ LENGTH                    09260000
         OI    BEDFLAG1,INEOF       SET EOF ENCOUNTERED                  09270000
READCLS  DS    0H                                                        09280000
         TM    DCBOFLGS,DCBOFOPN    IS DATA SET OPEN?                    09290000
         BC    ALLOFF,READF200      NO-                                  09300000
         SPACE 1                                                         09310000
         CLOSE ((R12))              CLOSE IT                             09320000
         SPACE 1                                                         09330000
         LR    R1,R12                COPY DCB ADDRESS                    09340000
         SPACE 1                                                         09350000
         FREEPOOL (1)                FREE QSAM BUFFERS                   09360000
         SPACE 1                                                         09370000
         SLR   R0,R0                SET LENGTH                           09380000
         B     READF300                                                  09390000
READSYN  DS    0H                                                        09400000
         SYNADAF ACSMETH=QSAM       REQUEST FORMATTED MESSAGE            09410000
         SPACE 1                                                         09420000
*        MVC   SYNADTXT,50(R1)      COPY MESSAGE TEXT                    09430000
         SPACE 1                                                         09440000
*        COMMSGS TEXT=MSG230        NOTIFY OPERATOR                      09450000
         SPACE 1                                                         09460000
         SYNADRLS                   RELEASE BUFFERS                      09470000
         SPACE 1                                                         09480000
         OI    BEDFLAG1,PERMIERR    SET PERMANENT INPUT ERROR            09490000
         B     READCLS              GO CLOSE IF NECESSARY                09500000
         SPACE 1                                                         09510000
*-------------------------------------------------------------------*  09520000
*        NORMAL RETURN                                               *  09530000
*-------------------------------------------------------------------*  09540000
         SPACE 1                                                         09550000
READF200 DS    0H                                                        09560000
         ST    R1.MOVESTAT+8        SAVE FOR SEGMENT ROUTINE             09570000
         ST    R0.MOVESTAT+12       SAVE                                 09580000
READF300 DS    0H                                                        09590000
         LM    R14,R1,SAVEREGS      RESTORE REGISTERS                    09600000
         BR    R5                                                        09610000
         SPACE 2                                                         09620000
*-------------------------------------------------------*                09630000
*        FIND SEGMENT ROUTINE                           *                09640000
*                                                       *                09650000
*        SUBROUTINE TO PROCESS THE HEADER RECORD AND PICK *              09660000
*        OUT THE DATA ELEMENT AND SEGMENT SEPERATORS TO  *                09670000
*        DYNAMICALLY MAKE TO TRANSLATE TABLES.           *                09680000
*                                                       *                09690000
*        INPUT  - R9   - RETURN ADDRESS                 *                09700000
*          MOVESTAT+ 0 - ADDRESS OF SEGMENT BUILD AREA  *                09710000
*          MOVESTAT+ 4 - LENGTH OF SEGMENT BUILD AREA   *                09720000
*          MOVESTAT+ 8 - ADDRESS OF ANSI/UNJEDI RECORD  *                09730000
*          MOVESTAT+12 - LENGTH OF ANSI/UNJEDI RECORD   *                09740000
*                                                       *                09750000
*-------------------------------------------------------*                09760000
         SPACE 3                                                         09770000
FINDSGMT DS    0H                                                        09780000
         XC    MOVESTAT(8),MOVESTAT RESET STATS OF BUILD AREA            09790000
         LM    R14,R15,MOVESTAT+8 GET WHERE LEFT OFF IN RECORD           09800000
         LTR   R15,R15              ANY BYTES LEFT TO PROCESS?           09810000
         BNP   FNDHSTRT             NO-                                  09820000
         BCTR  R15,0                YES- GET EXECUTABLE LENGTH           09830000
         LA    R5,TABLE01           GET TABLE ADDRESS                    09840000
         EX    R15,ENDALPHA         FIND SEGMENT ID                      09850000
         BZ    FNDS0080              NOT FOUND                           09860000
         LA    R15,1(R15,R14)        POINT PAST LAST BYTE OF RECORD      09870000
         LR    R14,R1                COPY ADDRESS OF SEGMENT ID          09880000
         SR    R15,R14               GET LENGTH LEFT                     09890000
FNDS0070 DS    0H                                                        09900000
         STM   R14,R15,MOVESTAT+8 RESET STATS                            09910000
         B     FNDHSTRT              CONTINUE                            09920000
FNDS0080 DS    0H                                                        09930000
         LA    R15,0                 SET ZERO BYTES LEFT OF THIS RECORD  09940000
         B     FNDS0070              CONTINUE                            09950000
FNDALPHA TRT   0(0,R14),0(R5)                                            09960000
FNDHSTRT DS    0H                                                        09970000
         ICM   R0,B'1111',MOVESTAT+12 FINISHED READING RECORD?           09980000
         BNZ   FNDS0090                NO-                               09990000
         SPACE 1                                                         10000000
         BAL   R5,READFILE             RETRIEVE NEXT INPUT RECORD        10010000
         TM    BEDFLAG1,INEOF          EOF REACHED?                      10020000
         BO    FNDH1300                YES-                              10030000
         SPACE 1                                                         10040000
         LM    R14,R15,MOVESTAT+8      GET RECORD ADDRESS/LENGTH         10050000
FNDS0090 DS    0H                                                        10060000
         ICM   R0,B'1111',MOVESTAT+4 FINISHED BUILDING RECORD?           10070000
         BNZ   FNDS0100                NO-                               10080000
         L     R1,BUFFER               NO- GET ADDRESS OF BUILD AREA     10090000
         ST    R1,MOVESTAT             SAVE IT                           10100000
         LA    R1,L'ERRBUFF            GET LENGTH OF BUILD AREA          10110000
         ST    R1,MOVESTAT+4           SAVE IT                           10120000
FNDS0100 DS    0H                                                        10130000
         CLC   SEP,0(R14)              NO- SEPARATOR?                    10140000
         BE    FNDH0900                YES-                              10150000
FNDS0500 DS    0H                                                        10160000
         LA    R14,1(R14)              NO- POINT TO NEXT BYTE            10170000
         BCT   R15,FNDS0100            PROCESS REST OF RECORD            10180000
FNDS0600 DS    0H                                                        10190000
         S     R1,MOVESTAT+12          UPDATE DISPLACEMENT OF SEPARATOR  10200000
         STH   R1,ELMTCTR              SAVE IT                           10210000
         LM    R14,R1,MOVESTAT         GET MOVE STATS                    10220000
         CR    R15,R1                  RECV LGTH > SEND LGTH?            10230000
         BNH   FNDHERR                 NO- ERROR                         10240000
         LR    R15,R1                  SET_RECV_LGTH TO SEND_LGTH        10250000
         MVCL  R14,R0                  MOVE TO RECORD BUILD AREA         10260000
         L     R15,MOVESTAT+4          GET MAX LGTH OF BUILD AREA        10270000
         S     R15,MOVESTAT+12         MINUS ACTUAL BYTES MOVE           10280000
         STM   R14,R1,MOVESTAT         SAVE MOVE STAT                    10290000
         B     FNDHSTRT                GO READ ANOTHER RECORD            10300000
FNDH0900 DS    0H                                                        10310000
         S     R14,MOVESTAT+8          CALC LGTH OF REST OF SEGMENT      10320000
         LA    R1,1(R14)               ADD_ONE_FOR_SEGMENT               10330000
         B     FNDH1000                GO MOVE TO BUILD AREA             10340000
FNDH1000 DS    0H                                                        10350000
         LM    R14,R0,MOVESTAT         SET UP FOR MOVE                   10360000
         CR    R15,R1                  RECV LGTH > SEND LGTH?            10370000
         BH    FNDH1100                YES-                              10380000
         LR    R1,R15                  NO- SET SEND LGTH TO RECV LGTH    10390000
         B     FNDH1200                                                  10400000
FNDH1100 DS    0H                                                        10410000
         LR    R15,R1                  SET RECV LGTH TO SEND LGTH        10420000
FNDH1200 DS    0H                                                        10430000
         LTR   R15,R15                 LENGTH POSITIVE?                  10440000
         BNP   FNDH1400                NO-                               10450000
         CH    R15,=H'256'             YES- TOO BIG?                     10460000
         BH    FNDH1400                YES-                              10470000
         MVCL  R14,R0                  MOVE TO RECORD BUILD AREA         10480000
         LR    R15,R0                  GET_ADDR_PAST_SEPERATOR           10490000
         S     R15,MOVESTAT+8          CALC BYTES MOVED                  10500000
         L     R1,MOVESTAT+12          GET TOTAL BYTES IN RECORD         10510000
         SR    R1,R15                  CALC RESIDUAL BYTE COUNT          10520000
         STM   R0,R1,MOVESTAT+8        SAVE_FOR_LATER                    10530000
         L     R15,BUFFER              GET BEGINNING OF RECORD           10540000
         SR    R14,R15                 CALC LENGTH OF RECORD             10550000
         LA    R14,4(R14)              ADD LENGTH OF RDW                 10560000
         L     R15,BUFFRDW             GET ADDRESS OF RDW                10570000
         STCM  R14,B'0011',0(R15)      SET RDW                           10580000
         B     FNDHNORM                RETURN                            10590000
FNDH1300 DS    0H                                                        10600000
         CLC   MOVESTAT+4(4),BEDZERO STILL BUILDING A SEGMENT?           10610000
         BE    FNDHEOF                 NO-                               10620000
         B     FNDHERR                 YES- END OF SEGMENT MISSING       10630000
FNDH1400 DS    0H                                                        10640000
         STM   R14,R1,MOVESTAT         SAVE REGISTERS                    10650000
         ABEND 8,DUMP                                                    10660000
         SPACE 1                                                         10670000
*----------------------------------------------------------------------* 10680000
*        +0    ERROR RETURN                                            * 10690000
*----------------------------------------------------------------------* 10700000
         SPACE 1                                                         10710000
FNDHERR  DS    0H                                                        10720000
         B     0(R9)                                                     10730000
         SPACE 1                                                         10740000
*----------------------------------------------------------------------* 10750000
*        +4    EOF RETURN                                              * 10760000
*----------------------------------------------------------------------* 10770000
         SPACE 1                                                         10780000
FNDHEOF  DS    0H                                                        10790000
         B     4(R9)                                                     10800000
         SPACE 1
*-----------------------------------------------------------------*
*        +8    NORMAL RETURN                                      *
*-----------------------------------------------------------------*
         SPACE 1
FNDHNORM DS    0H
         B     8(R9)
         SPACE 1
TABLE01  SCNTBL CHARSET=ALPHA,FUNC=LOCATE
         SPACE 1
TBABEND  DS    0H
         PUSH  USING
         DROP
         USING *,R15
         CH    R0,=H'12'               SDWA PRESENT?
         BNE   AAABEND1                YES-
*         RETURN TO RTM, ATTEMPTING RECOVERY:
         SPACE 1
         LA    R0,AAABEND2             POINT TO REINSTATEMENT ROUTINE
         LA    R15,4                   INDICATE TASK IS TO BE REINSTATED
         BR    R14                     RETURN TO RTM
         SPACE 1
AAABEND1 DS    0H
         STM   R14,R12,12(R13)         SAVE REGS
         LR    R10,R15                 SET BASE
         USING TBABEND,R10
         DROP  R15
         LR    R4,R1                   SDWA ADR
         USING SDWA,R4
         L     R2,SDWAPARM             GET BASE REGISTER
         USING EDITSBED,R2             GET ADDRESSABILITY
         LA    R3,2048(,R2)            SET 2ND BASE REG
         LA    R3,2048(,R3)
         USING EDITSBED+4096,R3
         ICM   R1,B'0111',SDWACMPC     GET COMPLETION CODE
         DROP  R4
         SRL   R1,12
         N     R1,=X'00000FFF'
         ST    R1,RTNCODE                SAVE IT
         SPACE 1
         SETRP REGS=(14,12),                                              +
               RC=4,RETADDR=AAABEND2,FRESDWA=YES,WKAREA=(4)
         SPACE 1
         POP   USING
         SPACE 2
AAABEND2 DS    0H
         LR    R10,R1                    SET BASE REGISTER
         LA    R11,2048(,R10)            SET 2ND BASE REG
         LA    R11,2048(,R11)
         L     R2,=A(ERROR12)            POINT TO RESTART ADDRESS
         BR    R2                        GO TO IT
         SPACE 1
         LTORG
         EJECT
*-----------------------------------------------------------------*
*        MISC DATA AREA                                           *
*-----------------------------------------------------------------*
         SPACE 1
ZUSER    DC    CL8' '
XLATOR   DC    A(0)

SAVEAREA DC    18F'0'
SAVEREGS DC    18F'0'
DBLWORD  DC    D'0'
BUFFRDW  DC    A(ERRRDW)               POINT TO RDW
BUFFER   DC    A(ERRBUFF)              POINTER TO ERROR BUFFER
MSGID    DC    CL8' '                  MESSAGE ID
DCBNAMES DC    AL2(L'IDCB+L'ODCB+L'EDCB)  LENGTH OF DDNAMES
IDCB     DC    CL8' '                  INPUT DCB FOR REBLOCK
ODCB     DC    CL8' '                  OUTPUT DCB FOR REBLOCK
EDCB     DC    CL8'REBLKERR'           SYSPRINT DCB FOR REBLOCK
ISPLADDR DC    A(0)
TEMPDSN  DC    C[illegible]
IDSN     DC    CL44' '
MOVESTAT DC    4F'0'
BEDZERO  DC    D'0'                    CONSTANT ZEROS
BEDBLANK DC    CL8' '                  CONSTANT BLANK
ELMTCTR  DC    H'0'
BEDFLAG1 DC    X'00'
INEOF    EQU   X'80'                   END OF FILE
PERMIERR EQU   X'40'                   ERROR READING INPUT FILE
SEP      DC    X'00'                   SEGMENT SEPARATOR
FLAG1    DC    X'00'                   MISC FLAG
INIT     EQU   X'80'                   INITIALIZING
         SPACE 1
*-----------------------------------------------------------------*
*        DYNAMIC ALLOCATION CONTROL BLOCKS                        *
*-----------------------------------------------------------------*
         SPACE 1
DYNRBP   DC    0F'0',X'80',AL3(DYNRB)
DYNRB    DC    XL(S99RBEND-S99RB)'00'
         ORG   DYNRB+S99RBLN-S99RB
         DC    AL1(S99RBEND-S99RB)
         ORG   DYNRB+S99VERB-S99RB
         DC    AL1(S99VRBAL)
         ORG   DYNRB+S99FLAG1-S99RB
         DC    AL1(S99NOCNV)
         ORG
SOALLOC  DC    A(TXTDD),AL1(128),AL3(TXTSO)
DSCONCLS DC    AL1(128),AL3(TXTCONC)
DSALLOCS DC    A(TXTDD,TXTDSN),AL1(128),AL3(TXTSHR)
DSALLOCO DC    A(TXTDD,TXTDSN),AL1(128),AL3(TXTOLD)
DSUNALOC DC    AL1(128),AL3(TXTDD)
DSUNCONC DC    AL1(128),AL3(TXTDDU)
DSALLOCN DC    A(TXTDD)
         DC    A(TXTDSN)
         DC    A(TXTNEW)
         DC    A(TXTNDISP)
         DC    A(TXTCDISP)
         DC    A(TXTUNITX)
         DC    A(TXTTRK)
         DC    A(TXTPRIME)
         DC    A(TXTSECND)
         DC    A(TXTRECFM)
         DC    A(TXTLRECL)
         DC    AL1(128),AL3(TXTBLKSZ)
TXTCONC  DC    AL2(DCCDDNAM,2,8),CL8' ',AL2(8)
TXTCONCX DC    CL8' '
TXTTRK   DC    AL2(DALTRK,0)
TXTNEW   DC    AL2(DALSTATS,1,1),X'04'
TXTNDISP DC    AL2(DALNDISP,1,1),X'02'
TXTCDISP DC    AL2(DALCDISP,1,1),X'04'
TXTRECFM DC    AL2(DALRECFM,1,1),X'40'
TXTLRECL DC    AL2(DALLRECL,1,2),X'0202'
TXTBLKSZ DC    AL2(DALBLKSZ,1,2),X'3C40'
TXTPRIME DC    AL2(DALPRIME,1,3),X'000096'
TXTSECND DC    AL2(DALSECND,1,3),X'000000'
TXTUNITX DC    AL2(DALUNIT,1,5),CL5'SPACE'
TXTOLD   DC    AL2(DALSTATS,1,1),X'01'
TXTDD    DC    AL2(DALDDNAM,1,8),CL8' '
TXTDDU   DC    AL2(DDCDDNAM,1,8),CL8' '
TXTDSN   DC    AL2(DALDSNAM,1,44),CL44' '
TXTSO    DC    AL2(DALSYSOU,1,1),C'W'
TXTSHR   DC    AL2(DALSTATS,1,1),X'08'
         SPACE 1
*---------------------------------------------------------------------*
*        SYSOUT DDNAME LIST                                           *
*---------------------------------------------------------------------*
         SPACE 1
SOLIST   DC      CL8'MONITOR'
         DC      CL8'MYOUT'
         DC      CL8'REPORT'
         DC      CL8'SYSOUT'
         DC      CL8'MPT'
         DC      CL8'SBG'
         DC      CL8'EEO'
         DC      CL8'JSP'
         DC      CL8'REBLKERR'
         DC      CL8' '
         SPACE 1
*---------------------------------------------------------------------*
*        DDNAME-DSNAME LIST FOR DISP=SHR                              *
*---------------------------------------------------------------------*
         SPACE 1
DSLIST   DC      CL8'ANSI'
DSNAT    DC      CL44' '
         DC      CL8'ANSIP'
DSNAP    DC      CL44' '
         DC      CL8'APPLOUT'
DSNXP    DC      CL44' '
         DC      CL8'APPLOUTX'
DSNXT    DC      CL44' '
         DC      CL8'CNT'
DSNCT    DC      CL44' '
         DC      CL8'CNTP'
DSNCP    DC      CL44' '
         DC      CL8'IDS'
DSNIT    DC      CL44' '
         DC      CL8'IDSP'
DSNIP    DC      CL44' '
         DC      CL8'COND'
DSNOT    DC      CL44' '
         DC      CL8'CONDX'
DSNOP    DC      CL44' '
         DC      CL8'VSAM',CL44'VAAEX.EDIS.D.TEST.RECOVERY'
         DC      CL8' '
         SPACE 1
*---------------------------------------------------------------------*
*        DDNAME-ALLOC LIST FOR DISP=SHR                               *
*---------------------------------------------------------------------*
         SPACE 1
DSLISTS  DC      CL8'SONLG',X'90',X'0050',X'1810',X'000005'
         DC      CL8' '
         SPACE 1
*---------------------------------------------------------------------*
```

```
*         DDNAME-ALLOC LIST FOR DISP=OLD                                   *
*-------------------------------------------------------------------------*
          SPACE 1
DSLISTO   DC    CL8'FAOUT',X'50',X'0800',X'5004',X'000032'
          DC    CL8'OUTPUT',X'50',X'0800',X'5004',X'000064'
          DC    CL8'TESTBED2',X'50',X'0C37',X'618C',X'000005'
          DC    CL8'TESTBED',X'50',X'0800',X'5004',X'000001'
          DC    CL8'REJECT';X'50';X'0804';X'5028',X'000028'
          DC    CL8'RECOV',X'50',X'0804',X'5028',X'000028'
          DC    CL8'STORE',X'90',X'0050',X'1810',X'000010'
          DC    CL8' '
          SPACE 1
*-------------------------------------------------------------------------*
*         DEFINITION OF PROGRAM STORAGE FOR PANEL VARIABLES               *
*-------------------------------------------------------------------------*
          SPACE 1
DSN       DC    CL44' '
DSNW      DC    CL44' '
DSNS      DC    CL44' '
DSNL      DC    CL44' '
STD       DC    CL8' '
RLS       DC    CL5' '
VERS      DC    CL12' '
AGCY      DC    CL2' '
REAS      DC    CL71' '
LASTSEG   DC    CL6' '
NUMB      DC    CL6' '
TRANDATA  EQU   STD,*-STD,C'C'
          DS    0F
RTNCODE   DC    CL4' '
REEZCODE  DC    CL2' '
DDERR     DC    CL8' '
          SPACE 1
*-------------------------------------------------------------------------*
*         DEFINITION OF ISPF SERVICE REQUESTS                             *
*-------------------------------------------------------------------------*
          SPACE 1
DISPLAY   DC    CL8'DISPLAY'
EDIT      DC    CL8'EDIT'
PRIMARY   DC    CL8'EDITB'
PANEL2    DC    CL8'EDITB1'
PANEL3    DC    CL8'EDITB2'
CONTROL   DC    C'CONTROL'
SELECT    DC    C'SELECT'
ERRORS    DC    C'ERRORS'
RETURN    DC    C'RETURN'
VDEFINE   DC    CL8'VDEFINE'
VGET      DC    CL8'VGET'
VPUT      DC    CL8'VPUT'
PROFILE   DC    CL8'PROFILE'
SHARED    DC    CL8'SHARED'
CHAR      DC    CL8'CHAR'
HEX       DC    CL8'HEX'
TBCREATE  DC    CL8'TBCREATE'
TBDISPL   DC    CL8'TBDISPL'
TBADD     DC    CL8'TBADD'
TBTOP     DC    CL8'TBTOP'
TBSARG    DC    CL8'TBSARG'
TBCLOSE   DC    CL8'TBCLOSE'
LOG       DC    CL8'LOG'
SETMSG    DC    CL8'SETMSG'
VARTABLE  DC    CL8'VARTABLE'
NOWRITE   DC    CL8'NOWRITE'
VARLIST   DC    C'(TBNUMB TBREAS)'
SAVLIST   DC    C'(TBDSN TBDSNW TBDSNS TBDSNAT TBDSNAP TBDSNCT TBDSNCP T*
                BDSNIT TBDSNIP TBDSNXT TBDSNXP TBDSNOT TBDSNOP TBDSNL)'
USERLIST  DC    C'(ZUSER)'
          SPACE 1
*-------------------------------------------------------------------------*
*         DEFINITION OF LENGTH OF PANEL VARIABLES                         *
*-------------------------------------------------------------------------*
          SPACE 1
LENGTH2   DC    F'2'
LENGTH4   DC    F'4'
LENGTH5   DC    F'5'
LENGTH6   DC    F'6'
LENGTH8   DC    F'8'
LENGTH11  DC    F'11'
LENGTH12  DC    F'12'
LENGTH44  DC    F'44'
LENGTH71  DC    F'71'
          SPACE 1
*-------------------------------------------------------------------------*
*         DEFINITION OF PANEL VARIABLES                                   *
*-------------------------------------------------------------------------*
          SPACE 1
SELCMD    DC    C'CMD(%EDITB)'
ZUSERLIT  DC    C'(ZUSER)'
DSNLIT    DC    C'(TBDSN)'
DSNWLIT   DC    C'(TBDSNW)'
DSNSLIT   DC    C'(TBDSNS)'
DSNLLIT   DC    C'(TBDSNL)'
DSNALIT   DC    C'(TBDSNAT)'
```

```
DSNALITP DC    C'(TBDSNAP)'                                                   13580000
DSNCLITT DC    C'(TBDSNCT)'                                                   13590000
DSNCLITP DC    C'(TBDSNCP)'                                                   13600000
DSNILITT DC    C'(TBDSNIT)'                                                   13610000
DSNILITP DC    C'(TBDSNIP)'                                                   13620000
DSNXLITT DC    C'(TBDSNXT)'                                                   13630000
DSNXLITP DC    C'(TBDSNXP)'                                                   13640000
DSNOLITT DC    C'(TBDSNOT)'                                                   13650000
DSNOLITP DC    C'(TBDSNOP)'                                                   13660000
STDLIT   DC    C'(TBSTD)'                                                     13670000
RLSLIT   DC    C'(TBRLS)'                                                     13680000
VERSLIT  DC    C'(TBVER)'                                                     13690000
AGCYLIT  DC    C'(TA)'                                                        13700000
REASLIT  DC    C'(TBREAS)'                                                    13710000
NUMBLIT  DC    C'(TBNUMB)'                                                    13720000
LASTLIT  DC    C'(TLASTS)'                                                    13730000
RTC      DC    C'(RTC)'                                                       13740000
REEZ     DC    C'(REEZ)'                                                      13750000
DD       DC    C'(DD)'                                                        13760000
         SPACE 1                                                              13770000
*----------------------------------------------------------------------*      13780000
*        DCB'S                                                          *     13790000
*----------------------------------------------------------------------*      13800000
         SPACE 1                                                              13810000
ERRDCB   DCB   DDNAME=TESTBEDZ,DSORG=PS,MACRF=GM                              13820000
         SPACE 1                                                              13830000
INPDCB   DCB   DDNAME=INPUT,DSORG=PS,MACRF=GL                                 13840000
         SPACE 1                                                              13850000
OUTDCB   DCB   DDNAME=SGMTFILE,DSORG=PS,MACRF=PM                              13860000
         SPACE 1                                                              13870000
STOREDCB DCB   DDNAME=STORE,DSORG=PS,MACRF=PM                                 13880000
         SPACE 1                                                              13890000
LOGDCB   DCB   DDNAME=LOG,DSORG=PS,MACRF=PM                                   13900000
         SPACE 1                                                              13910000
OUTDCBX  DCB   DDNAME=SGMTFILE,DSORG=PS,MACRF=GL                              13920000
         SPACE 1                                                              13930000
         LTORG                                                                13940000
         SPACE 1                                                              13950000
ERRRDW   DC    AL2(*-*,0)                                                     13960000
ERRBUFF  DS    XL3123               ERROR BUFFER RECORD                       13970000
BDMODNUM DC    CL8'MD00049'         EDI MOD NUMBER                            99999996
         END                                                                  99999999
```

What is claimed is:

1. A method for interactively translating electronic data interchange files, comprising the steps of:

(a) generating a plurality of displays for interactively controlling the translation of an electronic data interchange file;

(b) translating said electronic data interchange file until a translation error exists;

(c) displaying said translation error on at least one of said plurality of displays so that said translation error may be corrected interactively;

(d) correcting said displayed translation error in response to data entered on said at least one of said plurality of displays; and

(e) repeating steps (a) through (d) until no translation error exists.

2. The method of claim 1, wherein said electronic data interchange file comprises transaction data to be communicated from a sending computer to a receiving computer and said translating step occurs after communicating said electronic data interchange file to said receiving computer.

3. The method of claim 2, wherein said correcting step further comprises the steps of:

forming a segment file for containing a portion of said electronic data interchange file where said portion includes said translation error;

placing said portion of said electronic data interchange file into said segment file;

displaying said portion on said at least one of said plurality of displays for correcting said translation error; and

forming a working file comprising all correctly translated portions of said electronic data interchange file.

4. The method of claim 2, wherein said displaying and correcting steps occur interactively without the need to retranslate all previously translated portions of said electronic data interchange file.

5. The method of claim 1, further comprising the step of logging each of said translation error occurring during the translation of said electronic data interchange file.

6. The method of claim 1, further comprising the step of forming a working file of all correctly translated portions of said electronic data interchange file.

7. A programmable machine system for interactively translating business transaction data between a plurality of different dictionary-structured transaction formats, said machine system including a plurality of system components, said machine system comprising:

output circuitry for generating a plurality of visible signals corresponding to the status of translation of said business transaction data from one format to another predetermined format;

translation circuitry for translating said business transaction data into said predetermined format;

error detection and reporting circuitry for detecting the existence of a translation error and communicating said translation error to said output circuitry;

editing circuitry for interactively receiving corrections to said business transaction data and for modifying said business transaction data in response to said corrections generating corrected business transaction data; and

said translation circuitry translating said corrected business transaction data.

* * * * *